

14. (New) The electronically commutable motor of claim 9, wherein the switching off of the at least one of the electronic control unit and the at least one semiconductor output stage is carried out in a time-delayed manner.

15. (New) The electronically commutable motor of claim 9, wherein comparison of the nominal operating speed and the actual speed is initiated and carried out only after a run-up phase of a predefined duration has expired.

16. (New) The electronically commutable motor of claim 15, wherein the run-up phase can be initiated with a switching-on of at least one of the electronic control unit, the at least one semiconductor output stage, and the input of a setpoint value.

REMARKS

This Preliminary Amendment cancels without prejudice original claims 1 to 8 and claim 1 in the annex to the International Preliminary Examination Report, in the underlying PCT Application No. PCT/DE00/03194, and adds without prejudice new claims 9 to 16. The new claims conform the claims to U.S. Patent and Trademark Office rules and do not add new matter to the application.

In accordance with 37 C.F.R. § 1.121(b)(3), the Substitute Specification (including the Abstract, but without the claims) contains no new matter. The amendments reflected in the Substitute Specification (including Abstract) are to conform the Specification and Abstract to U.S. Patent and Trademark Office rules, to correct informalities and to include Substitute Pages in the annex of the International Preliminary Examination Report. As required by 37 C.F.R. § 1.121(b)(3)(iii) and § 1.125(b)(2), a Marked Up Version Of The Substitute Specification comparing the Specification of record and the Substitute Specification also accompanies this Preliminary Amendment. Approval and entry of the Substitute Specification (including Abstract) is respectfully requested.

uncovered in the underlying PCT Application. A copy of the Search Report accompanies this Preliminary Amendment.

The underlying PCT application also includes an International Preliminary Examination Report, dated November 26, 2001, and an annex. An English translation of the International Preliminary Examination Report and the annex accompanies this Preliminary Amendment.

Applicants assert that the subject matter of the present application is new, non-obvious, and useful. Prompt consideration and allowance of the application are respectfully requested.

Respectfully Submitted,

KENYON & KENYON

Dated: 3/15/02

By: [Signature]

Richard L. Mayer
(Reg. No. 22,490)

One Broadway
New York, NY 10004
(212) 425-7200

454769

which:] Brief Description Of The Drawings

Figure 1 shows a block diagram of the functional units of [the motor; and] an exemplary motor according to an embodiment of the present invention.

5

Figure 2 shows a characteristics field stored in the control unit according to an embodiment of the present invention.

10

Detailed Description

15

As the block diagram according to Figure 1 shows, the motor unit includes an electronic control unit STE which is assigned a comparator unit VE. For a desired continuous operation, a correspondingly adjusted setpoint value $N_{\text{setpointv}}$ is specified and provided to this control unit STE. Consequently, after a run-up phase, correspondingly dimensioned PWM control signals pwm are emitted to semiconductor output stages EST which energize the excitation windings of motor M according to the pulse widths of these PWM control signals pwm. An actual speed N_{actual} thereupon sets in at motor M that is detected [in a known manner] and supplied as a signal to a comparator unit VE which may be integrated into control unit STE.

20

25

[Stored in control] Control unit STE [is] stores a motor characteristic curve which allows the derivation of a nominal operating speed n_n for each setpoint value $N_{\text{setpointv}}$. This nominal operating speed n_n is obtained more or less exactly in the case of the predefined setpoint value $N_{\text{setpointv}}$ if control unit STE, semiconductor output stages EST and motor M are operating correctly, and no conditions exist which lead to a drop in actual speed

30

35

supplied to comparator unit VE, and a speed deviation $N - N_{\text{setpointv}}$ is calculated and supplied to the comparator unit VE.

expected nominal operating speed n_x , then a fault exists which can lead to an overload during continuous operation. Therefore, comparator unit VE generates a switch-off signal AB [with] via which control unit STE and/or semiconductor output stages EST can be switched off, as the contacts AB off in the electric circuit of supply voltage U_{batt} indicate.

If setpoint value $N_{setpointv}$ is changed, then PWM control signals pwm , and therefore actual speed N_{actual} of motor M change, as well. A correspondingly new nominal operating speed n_x is supplied to comparator unit VE, and the comparison is carried out in the same manner for the new continuous operation with altered speed.

The switch-off of control unit STE and/or of semiconductor output stages EST may also be initiated in a delayed fashion, in order to suppress spurious peaks in the derived and detected speed values.

Permissible speed deviation ΔN may also be made a function of the magnitude of predefined setpoint value $N_{setpointv}$ and the existing magnitude of supply voltage u_x . The comparison by comparator unit VE may be carried out continually during the continuous operation, or repeated at time intervals. In addition, the overload protection by the comparison and the shutdown may first be switched to effective after reaching the nominal operating speed specified by the setpoint value, i.e. after a predefined or predefinable run-up time has expired. In this context, the run-up time may be started with the switching-on,

value $N_{setpointv}$ to control unit STE.

control unit STE, is a function not only of existing supply voltage u_x with its limiting values u_1 and u_2 , but also of stored speeds n_{11} , n_{12} , n_{21} , n_{22} of the corner points of characteristics field KF, as the specification

5 $n_i = f(N_{\text{setpoint}}, u_1, u_2, n_{11}, n_{12}, n_{21}, n_{22})$ in the Figure indicates, and as is clarified later.

As the three-dimensional characteristics field KF according to Figure 2 shows, the voltage range from U_{max} to U_{min} is plotted in the x-direction, while the pulse width from pwm_{min} to pwm_{max} extends in the z-direction. In the exemplary embodiment, $U_{\text{max}} = 13\text{V}$ and $U_{\text{min}} = 8\text{V}$ are selected, and the pulse width has a range from $\text{pwm}_{\text{min}} = 60\%$ to $\text{pwm}_{\text{max}} = 100\%$. For the smallest supply voltage, given $\text{pwm}_{\text{min}} = 60\%$ and $\text{pwm}_{\text{max}} = 100\%$, nominal operating speeds of $n_{11} = 50 \text{ min}^{-1}$ and $n_{21} = 1800 \text{ mm}^{-1}$ result, while for the greatest supply voltage, given $\text{pwm}_{\text{min}} = 60\%$ and $\text{pwm}_{\text{max}} = 100\%$, nominal operating speeds $n_{12} = 150 \text{ min}^{-1}$ and $n_{22} = 2900 \text{ min}^{-1}$ result. These nominal operating speeds n_{11} to n_{22} define the four corner points P1 to P4 in three-dimensional characteristics field KF. The connecting lines between corner points n_{11} and n_{21} , n_{11} and n_{12} , n_{21} and n_{22} , and n_{12} and n_{22} , respectively, permit the formation of a grid which, for existing supply

25 voltages U_x and pulse width pwm_x [corresponding] corresponds to a setpoint value[.]. Formation of the grid allows the derivation of allocated nominal operating speeds n_i on straight line $n_{1x} - n_{2x}$. Thus, given a supply voltage of $U_x = 10.5\text{V}$ and a pulse width of approximately 87%, a nominal operating speed of approximately 1800 min^{-1} can be interpolated from characteristics field KF.

30 further read, a characteristics field KF valid for [it] the further read [it] stored [it] control unit [it]

As the three-dimensional characteristics field KF according to Figure 2 shows, supply voltage u_x having the voltage range from smallest supply voltage $u_1 = 8V$ to greatest supply voltage $u_2 = 13V$ is plotted in the x-direction. In the z-direction, pulse width pwm of the PWM control signals is predefined, which may extend from minimal pulse width $pwm_1 = 60\%$ to maximum pulse width $pwm_2 = 100\%$. Given a preselected load of the motor, four limit operation cases are ascertained with u_1 and pwm_1 , u_1 and pwm_2 , u_2 and pwm_1 , as well as u_2 and pwm_2 , which lead to nominal operating speeds $n_x = n_1, n_{12}, n_{21}$ and n_{22} , and consequently define characteristics field KF according to Figure 2.

If motor M is loaded with a different load, then a similar characteristics field KF results having new nominal operating speeds n_{11}, n_{12}, n_{21} and n_{22} .

The following values result for characteristics field KF of an exemplary embodiment shown in Figure 2:

$n_{11} = 50 \text{ min}^{-1}$ at $u_1 = 8V$ and $pwm_1 = 60 \%$
 $n_{12} = 150 \text{ min}^{-1}$ at $u_2 = 13V$ and $pwm_1 = 60 \%$
 $n_{21} = 1800 \text{ min}^{-1}$ at $u_1 = 8V$ and $pwm_2 = 100 \%$
 $n_{22} = 2900 \text{ min}^{-1}$ at $u_2 = 13V$ and $pwm_2 = 100 \%$

Characteristics field KF can be represented as a grid, the connecting lines between corner points n_{11} and n_{12} , and n_{21} and n_{22} , respectively, as well as n_{11} and n_{22} , and n_{12} and n_{21} , respectively, specifying the gridding, and as is shown, for an existing supply voltage u_x , permitting the

As grid line $nx_1 - nx_2$ shows, in the case of $u_x = 10.5V$ and a pulse width of $pwm_x \approx 87.5\%$, the derivation of nominal operating speed n_x leads to a value of approximately 1800 min^{-1} .

5

To calculate nominal operating speed n_x allocated to a setpoint value N_{setpoint} , one proceeds as follows with interpolated coefficients stg1, stg2 and stg3:

10

$$stg1 = \frac{n_{12} - n_{11}}{u_2 - u_1} \quad stg2 = \frac{n_{22} - n_{21}}{u_2 - u_1}$$

$$n_{1x} = n_{11} + stg1 * (u_x - u_1)$$

$$n_{2x} = n_{21} + stg2 * (u_x - u_1)$$

15

$$stg_3 = \frac{n_{2x} - n_{1x}}{pwm_2 - pwm_1} = \frac{n_{21} - n_{11} + (stg_2 - stg_1) * (u_x - u_1)}{pwm_2 - pwm_1}$$

[Therein:] Thus

$$n_x = n_{1x} + stg_3 * (pwm_x - pwm_1)$$

[stgi -

20

stg2

With the interpolated coefficients, we can calculate the nominal operating speed n_x for any setpoint value N_{setpoint} .

speed, but rather with its reciprocal value] Since the calculations use the reciprocal of the speed values, the above equation for calculating surface point n_x must be changed around accordingly. With $T_x = a/n_x$, it follows that:

$$\frac{a}{T_x} = n_{1x} + stg_3 * (pwm_x - pwm_1)$$

$$T_x = \frac{a * (pwm_1 - pwm_x)}{\left((stg_1 - stg_2) * u_x - n_{21} + n_{11} + (stg_2 - stg_1) * u_1 \right) * pwm_x + (pwm_1 * stg_2 - pwm_2 * stg_1) * u_x + pwm_1 * (n_{21} - u_1 * stg_2) + pwm_2 * (stg_1 * u_1 - n_{21})$$

10 In the formula above, only supply voltage U_x and the pulse width of output-stage control pwm_x are variable. The remaining factors may be stored as fixed parameters in the ROM or EEPROM. Following is once again the same formula with the variable names used in the program code.

15

$$v_{TX} = \frac{K_{ZAEHL_1}}{\left(\left(K_{NENN_1} * v_{ubat} + K_{NENN_2} \right) * v_{pwm_endst} + K_{NENN_3} * v_{ubat} + K_{NENN_4} \right)}$$

Wherein:

$$K_NENN_1 = (stg_1 - stg_2)$$

$$K_NENN_2 = -n_{21} + n_{11} + (stg_2 - stg_1) * u_1$$

$$K_NENN_3 = (pwm_1 * stg_2 - pwm_2 * stg_1)$$

$$K_NENN_4 = pwm_1 * (n_{21} - u_1 * stg_2) + pwm_2 * (stg_1 * u_1 - n_{11})$$

Abstract Of The Disclosure

An [The present invention relates to an] electronically commutatable motor, whose excitation windings are controllable via semiconductor output stages by an electronic control unit with the aid of PWM control signals, a setpoint value being specifiable to the control unit, and the control unit emitting corresponding PWM control signals to the semiconductor output stages; a motor characteristic curve, from which an assigned nominal operating speed is derivable for the setpoint value[,] being stored in the control unit, and the derived nominal operating speed being able to be compared to the actual speed of the motor[, and if]. If a predefinable or predefined speed difference between the nominal operating speed and the actual speed is exceeded, the control unit and/or the semiconductor output stages [is/are able to] can be switched off. The derivation of the nominal operating speed for the predefined setpoint value is facilitated by a three-dimensional characteristics field determined by four coordinate points.

458594

[Figure 1:

sc1lv = setpointv

5

ab = off

ist = actual]

[10191/2225]

ELECTRONICALLY COMMUTATABLE MOTOR

[Background Information] Field Of The Invention

The present invention relates to an electronically commutatable motor, whose excitation windings are controllable via semiconductor output stages by an electronic control unit with the aid of PWM control signals[, a]. A setpoint value [being specifiabile] can be specified to the control unit, and the control unit [emitting] emits corresponding PWM control signals to the semiconductor output stages[; a]. A motor characteristic curve, from which an assigned nominal operating speed is derivable for the setpoint value[, being] is stored in the control unit, and the derived nominal operating speed [being able to] can be compared to the actual speed of the motor[, and if]. If a predefinable or predefined speed difference between the nominal operating speed and the actual speed is exceeded, the control unit and/or the semiconductor output stages [is/are able to be switched off.] can be switched off.

[Such a motor is known from the German Patent]Background Information

A conventional electronically commutatable motor is described in German Published Patent Application 198 04 374 [A1]. In that case, the PWM control signals are established in their pulse width by the input of the setpoint value. The comparison of the nominal operating speed, which is assigned to the setpoint value, to the

width only gradually to the new value. Since the motor
 the nominal speed of the motor is a function of the motor

expenditure of memory in the control unit to ascertain the allocated nominal operating speed.

5 Storage of the characteristic-curve data of a motor in a
memory of the control unit and use of the
characteristic-curve data for deriving an operating value
is discussed to some extent in the U.S. Patent No.
5,901,236 and European Published Patent Application No. 0
10 386 057. In these references, a characteristics field
having a plurality of value pairs is used, from which the
desired nominal operating value can be derived by
interpolation onto a third coordinate. However, this
requires a considerable expenditure of memory,
15 particularly when the load of the motor changes.

The object of the present invention is to provide a motor
of the type mentioned at the outset with simple data in
the control unit, which, with minimal expenditure, for a
20 predefined load, significantly simplifies the derivation
of the nominal operating speed corresponding to a
predefined setpoint value.

Summary Of The Invention

25 According [This objective is achieved according] to the
present invention [in that], this objective is achieved
by storing the motor characteristic curve [is stored]
only as a three-dimensional characteristics field having
four corner points, which, through coordination with the
30 smallest pulse width and the limiting values of the
supply voltage, as well as with the largest pulse width

for the comparison to the actual speed is derivable as a
function of the existing supply voltage, the predefined

characteristics field.

In this context, advantage is taken of the fact that in many cases, the motor is always loaded with the same consumer, such as in the case of a fan drive. The four coordinate values of the characteristics field take into account not only the pulse widths of the PWM control signals corresponding to the predefinable setpoint values, but also the fluctuations of the supply voltage, and define a characteristics field which allows a clear and simple derivation, i.e. calculation of the assigned nominal operating speed, for the supply voltage present in each case and the control conditions, the connecting lines of the corner points of the characteristics field giving the stipulations for a grid, and thus facilitating the derivation of intermediate values in the coordinate directions for the supply voltage (e.g. x-coordinate) and the pulse widths (e.g. z-direction), and leading to the sought nominal operating speed (in the y-direction).

Depending upon the use of the motor, according to a further embodiment, the four corner points of the characteristics field may be determined for a predefined motor load. The motor can then be designed in a simple manner for a different load, i.e. consumer.

In this context, according to one refinement of the present invention, the comparison between the nominal operating speed and the actual speed is able to be carried out continually during the continuous running of the motor or repeated at time intervals.

being able to be supplied with a [more or less large] variable setting signal which is used for the emission

output stages. In addition, using this setting signal,
the allocated nominal operating speed may be derived on
the basis of the stored motor characteristic curve and
utilized for the comparison with the actual speed of the
motor arising. The actual speed of the motor may be
detected in various different ways [which are also
known].

For the comparison of the nominal operating speed and the
actual speed, the control unit is [preferably assigned]
coupled to a comparator unit which[, by preference, is]
may be integrated into the control unit.

So that the overload protection does not react to short
interference pulses of the actual-speed measurement, one
embodiment of the present invention provides for the
control unit and/or the semiconductor output stages to be
switched off in a time-delayed manner.

If a run-up phase precedes the continuous operation of
the motor, then the overload protection may be designed
so that the comparison of the nominal operating speed and
the actual speed is first able to be initiated and
carried out after a run-up phase of a predefined duration
has expired, so that an inadvertent shut-down does not
occur during this operating phase. The run-up phase may
be preset by the control unit, [it being possible to use]
and the amplitude of the pulses and the pulse width of
the PWM control signals, as well as their commutation
frequency [and the like] may be used as parameters. The
run-up phase of the motor is able to be initiated with

[The invention is explained more precisely with reference